



GPT-12000 Specifications

The specifications apply when the GPT-12000 is powered on for at least 30 minutes under +15°C~+35°C

GPT-12004 (Front)



GPT-12003/12002/12001 (Front)



GPT-12004 (Rear)



GPT-12003/12002/12001 (Rear)



(All models are available with optional GPIB or LAN)

Model \ Func.	AC Withstanding	DC Withstanding	Insulation Resistance	Ground Bond	Ground Continuity
GPT-12001	٧				٧
GPT-12002	٧	٧			٧
GPT-12003	٧	٧	٧		٧
GPT-12004	٧	٧	٧	٧	٧

AC WITHSTANDING		
Output-Voltage Range	0.050kV~5.000kV	
Output-Voltage Resolution	1V	
Output-Voltage Accuracy	± (1% of setting + 5V) [no load]	
Maximum Rated Load	200 VA (5kV/40mA)	
Maximum Rated Current	40mA (0.5kV< V \leq 5kV)	
	10mA (0.05 kV \leq V \leq 0.5kV)	
Output-Voltage Waveform	Sine wave	
Output-Voltage Frequency	50 Hz / 60 Hz selectable	
Voltage Regulation	\pm (1% + 5V) [maximum rated load \rightarrow no load]	
Voltmeter Accuracy	\pm (1% of reading + 5V)	
Current Measurement Range	1μA~40.00mA	
Current Best Resolution	1μΑ / 10μΑ	
Current Measurement Accuracy	\pm (1.5% of reading + 30 μ A)	
Current Offset	60μA Maximum	
Window Comparator Method	Yes	
ARC Detect	Yes	
RAMP UP (Rise Time)	0.1s~999.9s	

- 1	NO. 7-1, Jhongsing Road, Tucheng Dist	t., New Taipei City, 236, Taiwan
	(886) 2 2268-0389 F (886)2 2268-063	9 www.gwinstek.com

RAMP DOWN (Fall Time)	0.0s~999.9s		
TIMER (Test Time)	OFF, 0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
WAIT TIME	E(100ββπ + 20πs) 0.0s~999.9s		
GND	ON/OFF		
DC WITHSTANDING	ONYON		
Output-Voltage Range	0.050kV~6.000kV		
Output-Voltage Resolution	1V		
Output-Voltage Resolution Output-Voltage Accuracy	± (1% of setting + 5V) [no load]		
Maximum Rated Load	50W (5kV/10mA)		
Maximum Rated Current	$10\text{mA } (0.5\text{kV} < \text{V} \le 6\text{kV})$		
Naximum Rateu Current	,		
Voltage Regulation	$2mA (0.05kV \le V \le 0.5kV)$		
Voltage Regulation	± (1% + 5V) [maximum rated load → no load]		
Voltmeter Accuracy	± (1% of reading + 5V)		
Current Measurement Range	1μΑ~10.00mA		
Current Best Resolution	0.1μΑ /1μΑ /10μΑ		
Current Measurement Accuracy	±(1.5% of reading + 3μA) when I Reading < 1mA		
	\pm (1.5% of reading + 30 μ A) when I Reading \geq 1mA		
Current Offset	5μA Maximum		
Window Comparator Method	Yes		
ARC Detect	Yes		
RAMP UP (Rise Time)	0.1s~999.9s		
RAMP DOWN (Fall Time)	0.0s~999.9s		
TIMER (Test Time)	OFF, 0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
WAIT TIME	0.0s~999.9s		
GND	ON/OFF		
INSULATION RESISTANCE			
Output Voltage	50V~5000V dc		
Output Voltage Output-Voltage Resolution	50V		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy			
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display	50V ± (1% of setting + 5V) [no load]		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage	50V ± (1% of setting + 5V) [no load] Display Range		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V≤V≤100V	50V ± (1% of setting + 5V) [no load] Display Range 0.1ΜΩ~ 10.00GΩ		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage	50V ± (1% of setting + 5V) [no load] Display Range		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V≤V≤100V	50V ± (1% of setting + 5V) [no load] Display Range 0.1ΜΩ~ 10.00GΩ		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V≤V≤100V 150V≤V≤450V	$50V$ \pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim} 10.00G\Omega$ $0.1M\Omega^{\sim} 20.00G\Omega$		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V≤V≤100V 150V≤V≤450V 500V≤V≤5000V	$50V$ \pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim} 10.00G\Omega$ $0.1M\Omega^{\sim} 20.00G\Omega$		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage $50V \le V \le 100V$ $150V \le V \le 450V$ $500V \le V \le 5000V$ Resistance Measurement	50V ± (1% of setting + 5V) [no load] Display Range $0.1MΩ^{\sim} 10.00GΩ$ $0.1MΩ^{\sim} 20.00GΩ$ $0.1MΩ^{\sim} 50.00GΩ$		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage	$50V$ \pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim}$ 10.00GΩ $0.1M\Omega^{\sim}$ 20.00GΩ $0.1M\Omega^{\sim}$ 50.00GΩ Measurement Range / Accuracy		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim} 10.00G\Omega$ $0.1M\Omega^{\sim} 20.00G\Omega$ $0.1M\Omega^{\sim} 50.00G\Omega$ Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega$: \pm (5% of reading + 3 count)		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim}$ 10.00GΩ $0.1M\Omega^{\sim}$ 20.00GΩ $0.1M\Omega^{\sim}$ 50.00GΩ Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega$: \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}50M\Omega$: \pm (5% of reading + 1 count)		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	$\begin{array}{c} 50V \\ \pm \left(1\% \text{ of setting} + 5V\right) \left[\text{no load}\right] \\ \\ Display \text{Range} \\ 0.1 \text{M}\Omega^{\sim} 10.00 \text{G}\Omega \\ \\ 0.1 \text{M}\Omega^{\sim} 20.00 \text{G}\Omega \\ \\ 0.1 \text{M}\Omega^{\sim} 50.00 \text{G}\Omega \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\$		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim}$ 10.00GΩ $0.1M\Omega^{\sim}$ 20.00GΩ $0.1M\Omega^{\sim}$ 50.00GΩ Measurement Range / Accuracy $0.1M\Omega^{\sim}$ 1MΩ : \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}$ 50MΩ : \pm (5% of reading + 1 count) $50.1M\Omega^{\sim}$ 2GΩ : \pm (10% of reading + 1 count) $0.1M\Omega^{\sim}$ 1MΩ : \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}$ 500MΩ : \pm (5% of reading + 1 count)		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim}$ 10.00GΩ $0.1M\Omega^{\sim}$ 20.00GΩ $0.1M\Omega^{\sim}$ 50.00GΩ Measurement Range / Accuracy $0.1M\Omega^{\sim}1M\Omega$: \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}50M\Omega$: \pm (5% of reading + 1 count) $50.1M\Omega^{\sim}2G\Omega$: \pm (10% of reading + 3 count) $0.1M\Omega^{\sim}1M\Omega$: \pm (5% of reading + 1 count) $0.1M\Omega^{\sim}1M\Omega$: \pm (5% of reading + 1 count) $0.1M\Omega^{\sim}1M\Omega$: \pm (5% of reading + 1 count) $0.1M\Omega^{\sim}9.999G\Omega$: \pm (10% of reading + 1 count)		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim} 10.00G\Omega$ $0.1M\Omega^{\sim} 20.00G\Omega$ $0.1M\Omega^{\sim} 50.00G\Omega$ Measurement Range / Accuracy $0.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 50M\Omega : \pm (5\% \text{ of reading } + 1 \text{ count})$ $50.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 1 \text{ count})$ $0.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 1M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$ $1.1M\Omega^{\sim} 1M\Omega : \pm (2\% \text{ of reading } + 3 \text{ count})$		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim}$ 10.00GΩ $0.1M\Omega^{\sim}$ 20.00GΩ $0.1M\Omega^{\sim}$ 50.00GΩ Measurement Range / Accuracy $0.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}$ 50MΩ: \pm (5% of reading + 1 count) $50.1M\Omega^{\sim}$ 2GΩ: \pm (10% of reading + 1 count) $0.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 1 count) $1.1M\Omega^{\sim}$ 500MΩ: \pm (5% of reading + 1 count) $1.1M\Omega^{\sim}$ 500MΩ: \pm (5% of reading + 1 count) $1.0\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 1 count) $1.0\Omega^{\sim}$ 50GΩ: \pm (20% of reading + 1 count)* $1.0\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 1 count)*		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	\pm (1% of setting + 5V) [no load] Display Range $0.1M\Omega^{\sim}$ 10.00GΩ $0.1M\Omega^{\sim}$ 20.00GΩ $0.1M\Omega^{\sim}$ 50.00GΩ Measurement Range / Accuracy $0.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}$ 50MΩ: \pm (5% of reading + 1 count) $50.1M\Omega^{\sim}$ 2GΩ: \pm (10% of reading + 1 count) $0.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 1 count) $1.1M\Omega^{\sim}$ 500MΩ: \pm (5% of reading + 1 count) $1.1M\Omega^{\sim}$ 500MΩ: \pm (5% of reading + 1 count) $1.1M\Omega^{\sim}$ 500MΩ: \pm (20% of reading + 1 count) $1.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 1 count) $1.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 3 count) $1.1M\Omega^{\sim}$ 1MΩ: \pm (5% of reading + 1 count)		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V			
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V	$ \begin{array}{c} 50V \\ \pm \ (1\% \ of \ setting + 5V) \ [no \ load] \\ \\ Display \ Range \\ 0.1M\Omega^{\sim} \ 10.00G\Omega \\ 0.1M\Omega^{\sim} \ 20.00G\Omega \\ \\ 0.1M\Omega^{\sim} \ 50.00G\Omega \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\$		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V 500V ≤ V ≤ 450V			
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V 500V ≤ V ≤ 450V Voltage Regulation Voltmeter Accuracy			
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V 500V ≤ V ≤ 450V Voltage Regulation Voltmeter Accuracy Short-Circuit Current	box		
Output Voltage Output-Voltage Resolution Output-Voltage Accuracy Resistance Display Test Voltage 50V ≤ V ≤ 100V 150V ≤ V ≤ 450V 500V ≤ V ≤ 5000V Resistance Measurement Test Voltage 50V ≤ V ≤ 450V 500V ≤ V ≤ 450V Voltage Regulation Voltmeter Accuracy			

No. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

RAMP UP (Rise Time)	0.1s~999.9s		
RAMP DOWN (Fall Time)	0.0s~999.9s		
TIMER (Test Time)	OFF, 0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
WAIT TIME	0.0s~999.9s		
GND	ON/OFF		
Ground Bond			
Output-Current	03.00A~32.00A ac		
Output-Current Resolution	0.01A		
Output-Current Accuracy	3A≦I≦8A : ±(1% of reading + 0.2A)		
	8A <i≦32a +="" 0.05a)<="" :="" of="" reading="" td="" ±(1%=""></i≦32a>		
Test-Voltage	8Vac max (open circuit)		
Test-Voltage Frequency	50Hz/60Hz selectable		
Ohmmeter Measurement Range	1m Ω ~ 650m Ω		
Ohmmeter Measurement Resolution	0.1mΩ		
Ohmmeter Measurement Accuracy	\pm (1% of reading + 2 m Ω)		
Window Comparator Method	Yes		
TIMER (Test Time)	0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
Test Method	Four Terminal		
GND	ON/OFF		
Continuity Test			
Output-Current	100mA dc (fixed)		
Ohmmeter Measurement Range	0.10Ω~ 70.00Ω		
Ohmmeter Measurement Resolution	0.01Ω		
Ohmmeter Measurement Accuracy	\pm (10% of reading + 2 Ω)		
Window Comparator Method	Yes		
TIMER (Test Time)	0.3s~999.9s		
TIMER Accuracy	±(100ppm + 20ms)		
MEMORY			
Single Step Memory	MANU: 100 blocks		
Automatic Testing Memory	AUTO: 100 blocks, manu per auto: 10		
INTERFACE			
REMOTE (Front) terminal	Standard		
USB host (Front)	Standard		
Rear Output	Standard		
RS-232C	Standard		
USB device	Standard		
Signal I/O	Standard		
GPIB	Option		
LAN	Option		
DISPLAY			
	7" color LCD		
POWER SOURCE			
	AC 100V~240V ± 10%, 50Hz/60Hz		
	Power consumption : 400VA max.		
DIMENSION & WEIGHT			
DIMENSION & WEIGHT GPT-12001/12002/12003	380(W) x 148(H) x 436(D) mm; Approx. 11kg		

^{*} When Ground Mode is "ON", the measurement range is 30GΩ max. and adding 10% error for accuracy.